CASED VERSI ON OF ULI

1.0 Indicators

RED (left)	Power ON
YELLOW	Activity on the RS232 input
GREEN	RF Transmit (PTT)
RED (right)	DTMF tone detected or local TX to internet

2.0 Transmit Controls

VOIP TX	This over-rides the RX squelch when using COS to allow the local mic to talk to the stations connected on the Internet. Note that if RX VOX has been selected in Echolink this button does not do anything**.**
RF TX	Operates the RF Transmitter PTT to allow local mic to talk on the radio. This button will also cancel the current RF transmission if pressed while the transmitter is ON.
BOTH	Transmits simultaneously to the Internet and radio. The RF transmit will latched and is held until the VOIP button is released